

# MixPre Series

Audio Recorder | Mixer | USB Interface

SOUND DEVICES



Kashmir™ Bluetooth® SMART

ワールドクラスのサウンドクオリティと耐久性をあわせ持つ MixPre シリーズは軽量、高精細オーディオレコーダーであるだけでなく、USB オーディオストリーミングにも対応しています。MixPre シリーズの Kashmir と名付けられたマイクロフォン・プリアンプは、Sound Devices により設計された、ハイパフォーマンス、超低ノイズ、ディスクリート、Class-A マイクプリアンプです。MixPre シリーズは、サウンド・デザイナー、Pod キャスト、ビデオグラファー、ユーチューバー、フィールド録音技術者に最高のレコーダーです。



## MixPre-10T

タイムコード機能付マルチチャンネルレコーダー

- ・ 10 Inputs / 12 Tracks
- ・ Broadcast WAV ファイルを SD カードに録音
- ・ USB ポートのサムドライブにバックアップ・コピー
- ・ 内蔵タイムコードジェネレーター
- ・ 8つの超低ノイズ Kashmir マイクプリアンプ
- ・ 直観的なオペレーション
- ・ ユーザー設定可能なショートカット・スイッチ
- ・ ポータビリティ性に優れる柔軟な電源



## MixPre-6

オーディオレコーダー | USB インターフェース

- ・ 6 Inputs / 8 Tracks
- ・ WAV ファイルを SD カードに録音
- ・ 録音しながら USB ストリーム伝送
- ・ マルチトラック USB インターフェース
- ・ タイムコード・リーダー機能
- ・ レコード・トリガー機能
- ・ ユーザー設定可能なショートカット・ボタン
- ・ ポータビリティ性に優れる柔軟な電源



## MixPre-3

オーディオレコーダー | USB インターフェース

- ・ 3 Inputs / 5 Tracks
- ・ WAV ファイルを SD カードに録音
- ・ 録音しながら USB ストリーム伝送
- ・ マルチトラック USB インターフェース
- ・ タイムコード・リーダー機能
- ・ レコード・トリガー機能
- ・ ポータビリティ性に優れる柔軟な電源

# MixPre Series

Audio Recorders with USB Audio Interface

## 仕様

MIXPRE SERIES COMPARISON CHART	MixPre-10T	MixPre-6	MixPre-3
User/Application	For production sound mixers and field recordists	For field recording, podcasters, sound designers, and YouTubers.	For videographers, podcasters, YouTubers and field recordists
Tracks	12 (10 + mix)	8 (6 + mix)	5 (3 + mix)
Balanced Mic/Line Inputs	8 XLR/TRS combo	4 XLR/TRS combo	3 XLR
Aux/Mic In (3.5 mm) 4 uses: Plug-in-Power Mic, 2-ch Line In, Camera Return & Timecode	✓	✓	✓
Outputs	LR TA3, Stereo Line & HP	Stereo Line & Stereo HP	Stereo Line & Stereo HP
Auto-copy to USB Thumbdrive	✓	-	-
Max Sampling Rate	192kHz	192kHz	96kHz
USB Audio Streaming <small>Note: Maximum streaming on all models is 2 in/2 out from Windows w/o ASIO driver.</small>	12 in/4 out from Mac &/or Windows with ASIO® driver	8 in/4 out from Mac &/or Windows with ASIO® driver	5 in/2 out from Mac &/or Windows with ASIO® driver
Wingman iOS & Android app (via integrated Bluetooth Smart)	✓	✓	✓
Sunlight-Readable Touchscreen	✓	✓	✓
Multi-function Star Shortcut(s)	2 (via switch)	1 (via button)	-
Ergonomic Channel Knobs   Transport Controls	✓   Joystick w/LED Ring	✓   Backlit Buttons	✓   Backlit Buttons
Built-in TC Generator	✓ (Free Run, Rec Run)	-	-
TC Reader	Time of Day, Camera or LTC via BNC or Aux In	Time of Day, Camera or LTC via Aux In	Time of Day, Camera or LTC via Aux In
Word Clock	✓	-	-
48V Phantom	✓	✓	✓
Input Limiters	Analog	Analog	Analog
Output Limiters	Digital	Digital	Digital
Pair Linking	Pairs 1-2, 3-4, 5-6, 7-8, 9-10 (Stereo and/or M/S)	Pairs 1-2, 3-4, 5-6 (Stereo and/or M/S)	Pair 1-2 (Stereo and/or M/S)
Multichannel Linking	1-3, 1-4, 1-5, 1-6, 1-7, 1-8, 5-7, 5-8	1-3, 1-4	-
Input Delay   Input Polarity Reverse	✓   ✓	✓   ✓	✓   -
Input SOLOs (Individual or Multiple)	✓	✓	✓
Internal Slate Mic   Tone Generator	✓   ✓	-   ✓	-   ✓
Record Start / Stop Triggers	✓ (Flag or Timecode)	✓ (Flag or Timecode)	✓ (Flag or Timecode)
Punch In/Out (Overdub)	(via Musicians Plug-in)	(via Musicians Plug-in)	(via Musicians Plug-in)
Reverb & Vocal Air Effects	(via Musicians Plug-in)	(via Musicians Plug-in)	(via Musicians Plug-in)
Metronome	(via Musicians Plug-in)	(via Musicians Plug-in)	(via Musicians Plug-in)
Render (Export) Stereo Mix (.wav or .aac) Multichannel (.wav)	(via Musicians Plug-in)	(via Musicians Plug-in)	(via Musicians Plug-in)
Cue Points	✓	✓	✓
User-Programmable Headphone Presets	✓	✓	✓
Mounting	1/4-inch, 20-thread	1/4-inch, 20-thread	1/4-inch, 20-thread
Powering	10-17V Hirose, 8x AA, L-mount	4 or 8x AA, L-mount, USB	4 or 8x AA, L-mount, USB
Size (W x D x H)	8.15 x 6.88 x 1.40 inches (207mm x 175mm x 36mm)	6.53 x 4.65 x 1.40 inches (166mm x 118mm x 36mm)	5.68 x 4.35 x 1.40 inches (144mm x 110mm x 36mm)

## アクセサリ



**MX-8AA**

単三電池 8 本収納  
(All MixPre models)



**MX-4AA**

単三電池 4 本収納  
(MixPre-3 & 6 Only)



**MX-LMount**

Li-ion 充電電池 2 個  
(All MixPre models)



**XL-WPH3**

AC アダプター  
(MixPre 10T Only)



**WINGMAN™**

### ワイヤレス接続

MixPre- 3, 6, 10T は Bluetooth 通信機能を内蔵しており、iOS と Android 端末用のフリーソフト WINGMAN からレベルメータの監視、トランスポートのリモートコントロールができます。



**XL-2**

TA3-XLR オス変換ケーブル (63cm)。 (MixPre-10T Only)



**SAM-32SD**

32GB SD/SDHC card.  
(90MB/s for read and write speeds)



**MX-USBY**

USB-C コネクター  
(1x USB-C, 2x USB-A)  
(MixPre-3, 6 に同梱)



**MX-PSU**

AC アダプター  
(MixPre 3 & 6 Only)

**tt** 日本テックトラスト株式会社

URL: [www.tech-trust.co.jp](http://www.tech-trust.co.jp)  
〒150-8512 東京都渋谷区桜丘町 26-1  
セルリアンタワー15 階